

T1000LE

General Information

Model number: PA8007U (FCC ID# CJ6UK376)
Dimensions: 12.2"W x 10"D x 1.9"H
Weight: 6.5 lbs.
Voltage: Computer DC input - 12VDC, 1.7 A (+ = core; - = shell)
Battery: Universal AC adapter - 100-240 VAC, 50-60Hz
Removable rechargeable NiCD battery pack
CPU: 80C86 (9.54/4.77MHz)
RAM memory: 1MB standard (640KB conventional; 384KB LIM-EMS 3.2 or Hard-RAM)
Memory expandable up to 9MB via one credit card style memory slot when optional 1MB, 2MB, 4MB, or 8MB card is added
Video RAM: 32KB
Number of keys: 82
Keyboard type: 101-key keyboard compatible
Drives: One 1.44MB 3.5" floppy disk drive
One 20MB hard disk drive
Standard features: AutoResume
Double scan CGA
HardRAM
Auto display and hard drive shutdown
Intelligent power supply with "Gas Gauge"
Operating system included: Toshiba MS-DOS 3.30

Software Compatibility

Compatible with software written for the IBM PC/XT using CGA or T3100/AT&T 6300 640 x 400 high resolution graphics mode

Interfaces

RS-232-C serial port
Parallel printer/external diskette drive port
Built-in modem slot - "D" form factor
100 pin expansion Interface connector
Credit card style memory slot

Fluorescent Sidelit Supertwist LCD Display

Display area: 7.75"W x 4.88"H; 9" diagonal
Resolution: 640 x 400
Contrast: 4 : 1

2.5" 20MB Hard Disk Drive

Conner Peripherals HDD: CP2024
Interface: IDE
Average Access Time: 23ms
Recording Method: 2-7 RLL

Soft Switches

- 1) Change CPU speed
Fn + PgUp 9.54MHz CPU Speed
Fn + PgDn 4.77MHz CPU Speed
- 2) Character font

Fn + Right Arrow	Toggles display font
3) Pop-up window	
Fn + Esc	Toggles pop-up window
4) Keypad overlay	
Fn+ F10	Toggles keypad overlay and numlock
5) Fn key	
Fn + F11	Activates Num Lock
Fn + F12	Activates Scroll Lock
Fn + Ctrl	Simulate IBM enhanced keyboard Right Ctrl
Fn + Alt	Simulate IBM enhanced keyboard Right Alt
Fn + Enter	Simulate IBM enhanced keyboard numeric keypad

Enter

Hardware Switches and Controls

- 1) Power on/off
With display open located above keyboard on left side
- 2) Reset
Located on left side of computer
- 3) LCD brightness and contrast dials
Located on right side of display

Environmental Specifications

- 1) Operating condition

Ambient temperature:	41 to 95 degrees F.	5 to 35 degrees C.
Relative Humidity:	20% to 80% non-condensing	
Altitude (from sea level):	0 to 12,000 ft. (0 to 3000 meters)	
- 2) Non-Operating condition

Ambient temperature:	-4 to 140 degrees F.	-20 to 60 degrees C.
Relative Humidity:	8% to 80% non-condensing	
Altitude (from sea level):	40,000 ft (12,192 meters) max.	
- 3) Wet bulb temperature condition

Ambient temperature:	79 degrees F. (26 degrees C.) maximum
----------------------	---------------------------------------

Options and Extra Accessories

PC-PA8311U	1MB memory card (no longer manufactured)
PC-PA8312U	2MB memory card (no longer manufactured)
PC-PA2000U	2MB memory card (no longer manufactured)
PC-PA2001U	4MB memory card (no longer manufactured)
PC-PA2002U	8MB memory card (no longer manufactured)
PC-T24D	2400 bps Hayes compatible dedicated built-in modem (Bell or CCITT)
PC-T24D/F	2400bps data/9600bps send/receive FAX built-in modem (no longer manufactured)
PC-T144D/F	14400 bps send receive FAX built-in modem (no longer manufactured)
PC-T24D/X or PC-T24D/X2	2400 bps Hayes compatible dedicated built-in modem w/enhanced protocol (MNP5, V.42 bis) (both no longer manufactured)
PC-TCL24A	Audiovox Axsys cellular connection for use with T24D/X modem (no longer manufactured)

PC-TCL24M Motorola Axsys cellular connection for use with T24D/X
 modem (no longer manufactured)
 PC-TCL24N NEC Axsys cellular connection for use with T24D/X
 modem(no longer manufactured)
 PC-TCL24U Uniden Axsys cellular connection for use with T24D/X
 modem (no longer manufactured)
 PC-PA7225U 5.25" 360KB external FDD with 18VDC adapter
 PC-PA8705U Battery pack - 2200 mAh (no longer manufactured)
 PC-PA8712URA Battery pack - 1700 mAh
 PC17-PA8719U Modem slot battery pack (no longer manufactured)
 PC-PA8704U Battery pack recharger with AC adapter (no longer
 manufactured)
 PC-PA8706U Universal AC adapter
 PC-PA8717U 12VDC automobile adapter (no longer manufactured)
 PC-PA801L Statpower Prowatt 125 auto adapter
 PC-PA7367 Floppy Link to 5.25 desktop diskette drive (no longer
 manufactured)
 PC-PA8600U Desk Station 11 (no longer manufactured)
 PC13-PA872L Fabric carrying case (no longer manufactured)
 PC13-PA873L Fabric carrying case (no longer manufactured)
 PC-PA1000L Leather carrying case (no longer manufactured)
 PC-PA1050L Leather attach, case
 PC13-PA874L Executive leather portfolio (no longer manufactured)
 PR-PA2750U ExpressWriter 201 portable printer (no longer
 manufactured)
 PC-SW004 Toshiba BASIC 3.30 (no longer manufactured)
 PC-SW008 Toshiba MS-DOS 3.30 (no longer manufactured)
 PC-SW007 Toshiba MS-DOS 4.01 (no longer manufactured)
 PC-SW013 Toshiba MS-DOS 5.0 (no longer manufactured)
 PC-SW015 Toshiba MS-DOS 5.0 (no longer manufactured)